klik

65W USB-C™ Power Bank

20000mAh

Model No.: KPBUC20

Version 1.2

Power Bank Layout

1. USB-A QC 3.0 Output
2. USB-C PD Input/Output
3. Capacity LED Indicators
4. Power On/Off

Suitable for

- MacBook, MacBook Air, MacBook Pro 13" & 15" with USB-C charging
- USB-C charging laptops, ultrabooks & Chromebooks from HP, Dell, Lenovo, Acer, Asus, Google & Microsoft
- iPhone, iPad, smartphone, tablet, smartwatch & other USB devices

Features

- 20000mAh capacity can provide a full charge for an average 13" laptop
- 65W of power delivers fast, safe & optimal charging for your laptop
- USB-C PD port can fast charge the latest iPhone & iPad Pro models as well as the latest smartphones from Samsung, Google, Huawei & more
- Quick Charge 3.0 USB-A port ensures fast charging for your smartphone, tablet or other USB devices
- 65W input power allows recharging of the power bank in under 2 hours*
- Safe to carry on as hand luggage on flights (under the 100Wh limit)
- Rechargeable more than 500 times
- Four LED indicators to show remaining capacity
- Includes 30cm USB-C to USB-C & 30cm USB-A to USB-C cables
- Built-in over charging and short circuit protection
- Watt Hour Rating: 74Wh
- USB-C Input: DC 5V 2.4A / 9V 3A / 12V 3A / 15V 3A / 20V 3.25A (Max 65W)
- USB-C Output: DC 5V 2.4A / 9V 3A / 12V 3A / 15V 3A / 20V 3.25A (Max 65W)
- USB-A Output: DC 5V 3A / 9V 2A / 12V 1.5A (Max 18W)
- Total Output: USB-C 65W + USB-A 18W (Max 83W)
- Charging Time: 2 hours with 65W charger or 2.5 hours with 45W charger
- Size: 171m (L) x 79mm (W) x 23mm (H)
- Weight: 567g
- Certifications: RCM, RoHS, UN38.3

To Charge Power Bank

- For fastest charging times, use the included USB-C to USB-C cable and charge the power bank using your original MacBook charger or original USB-C laptop charger
- You can also charge the power bank using the included USB-A to USB-C cable and charge using a standard USB wall charger. However this can take up to 12 hours to fully charge the power bank
- During charging the LED indicators will flash
- When charging is complete the LED indicators will be permanently on

To Charge MacBook or USB-C Laptop

- Using the included USB-C to USB-C cable connect the USB-C port on the power bank to the USB-C port on your MacBook or laptop
- Press the On/Off button to start charging

To Charge iPhone or Smartphone

- To fast charge the latest iPhone use a certified USB-C to Lightning cable and connect the USB-C port to the power bank and the Lightning connector to your iPhone
- To fast charge the latest iPad Pro or Samsung or Google smartphone, use the included USB-C to USB-C cable and connect the USB-C port on the power bank to your device
- To charge a smartphone, tablet or other USB device, use the device's own charging cable and connect the USB-A port on the power bank to your device. Charging should start automatically
- If charging doesn't start, press the On/Off button to start charging

To Check Remaining Capacity

- Press On/Off button and LEDs will light to show remaining capacity
- The LEDs will turn off automatically after about 5 seconds

LED ● On / ○ Off / ◉ Flashing	Remaining Capacity
◉ ○ ○ ○	Less than 5%
● ○ ○ ○	5% to 25%
● ● ○ ○	25% to 50%
● ● ● ○	50% to 75%
● ● ● ●	75% to 100%

Important Safety Instructions

- To maximize battery life span, fully charge the power bank before first use
- Store power bank in a cool and dry place.
- Do not store power bank in hot or humid environment
- Operating temperature should be between -10°c to 45°c
- If power bank is not used for long periods of time, you should charge and discharge once every three months
- When charging a device, the power bank may feel warm, this is a normal operating condition and should not be cause for concern
- In normal conditions, the battery performance will decline over several years
- Do not dispose of power bank in heat or fire
- Do not clean power bank with harmful chemicals or detergents
- Misuse, dropping or excessive force may cause product damage

* When using a 65W USB-C wall charger

iPhone, iPad, iPod, Lightning, MacBook and MacBook Pro are trademarks of Apple Inc., registered in the U.S. and other countries. USB-C is a trademark of USB Implementers Forum.
Klik and the Klik logo are trademarks of Comsol Pty Ltd.

Li-ion RoHS

www.comsol.com.au

Made in China